

Model Name Beam Up & Down 150
 Materials Aluminium frame, PC diffuser
 Design by Peter Danczkay

Luminaire dimensions 150x3x5 cm
 Profile dimensions 30x50 mm
 Luminaire weight 1.8 kg

Light Direction Up & Down



Net Lumens output 6005 lm
 Lumens LED output 10005 lm
 Voltage (constant voltage) 24 V
 Amperes / Watts 2.8 A / 67 W



LED Life 50 000 hrs L80/B30
 Warranty 1+2 years



Technical data is subject to change. Document version v220415

Light Direction 	In --> BI	Down --> BD							
	Out --> BO	In & Out --> BH							BV
	Up --> BU	Up & Down --> BV							

Size 	Standard Sizes *								
	100 cm --> 100	150 cm --> 150							150
	200 cm --> 200	250 cm --> 250							

* Other sizes available upon request

Finish 	Premium --> P								
	Deco Black 10 10M	Pearl White 20 20M	Golden Eye 30 30M	Silver Chalice 40 40M	Ruby Red 50 50M	Twilight Blue 60 60M	Champagne Brown 70 70M	Forest Green 80 80M	

* Use XX for high gloss finish and XXM for matt

** Additional custom colours can be selected by providing RAL or auto colour code

Highline	--> H								
	Gold --> R1036	White --> R9016							HR9011
	Silver --> R1036	Black --> R9011							

* Use M suffix for matt

** Any RAL colour, or special effects Powder coating available upon request

LED Colour 	Warm White (Standard) - 3000°K --> 9300	Full Colour --> RGB		9400
	Extra Warm White - 2700°K --> 9270	Colour & Warm White --> R930		
	Neutral White - 4000°K --> 9400	Colour & Neutral White --> R940		
	Tuneable white - 2700°K-4000°K --> 2740	* Contact us for other requirements *		

Mounting 	* Canopy:			Floor Standing:			
	Single Point --> CS			Marble Base --> FM			
	Multiple Point --> CM			Granite Base --> FG			
	Vertical --> CV			Thick Aluminium Base --> FA			MM
				Thin & Wide Steel Base --> FS			
	* Recessed No Canopy:			Direct surface mounting:			
	Multiple Point --> MM			Flush Mount --> D0			
	Vertical --> MV			** Foot Mount --> DF			
	* Cable Length			** Foot Length			
	2.5m --> 025			6cm --> 6			025
4m --> 040			12cm --> 12				
6m --> 060							

Control 	Dimmable - W/o Dimmer --> 00	1-10V --> 40		
	Simple Remote --> 10	0-10V --> 50		20
	DALI / Push dim compatible --> 20	Casambi --> 60		
	DMX --> 30			

Full model number example



BV150 - HR9011 9400 - MM025 - 20