

Model Name Beam Up 150
 Materials Aluminium frame, PC diffuser
 Design by Peter Danczkay

Luminaire dimensions 150x3x3 cm
 Profile dimensions 30x27 mm
 Luminaire weight 1 kg

Light Direction Up



LED Life 50 000 hrs L80/B30
 Warranty 1+2 years



Net Lumens output 3000 lm
 Lumens LED output 5005 lm
 Voltage (constant voltage) 24 V
 Amperes / Watts 1.5 A / 34 W

Technical data is subject to change.

Document version v220415

	Light Direction	In --> BI	Down --> BD						
		Out --> BO	In & Out --> BH			BU			
		Up --> BU	Up & Down --> BV						

	Size	Standard Sizes *							
		100 cm --> 100	150 cm --> 150	150					
		200 cm --> 200	250 cm --> 250	250					

* Other sizes available upon request

	Finish	Premium --> P							
		Deco Black 10 10M	Pearl White 20 20M	Golden Eye 30 30M	Silver Chalice 40 40M	Ruby Red 50 50M	Twilight Blue 60 60M	Champagne Brown 70 70M	Forest Green 80 80M

* Use XX for high gloss finish and XXM for matt

** Additional custom colours can be selected by providing RAL or auto colour code

Highline --> H									
Gold --> R1036	White --> R9016							HR9011	
Silver --> R1036	Black --> R9011								

* Use M suffix for matt

** Any RAL colour, or special effects Powder coating available upon request

	LED Colour	Warm White (Standard) - 3000°K --> 9300	Full Colour --> RGB	9400
		Extra Warm White - 2700°K --> 9270	Colour & Warm White --> R930	
		Neutral White - 4000°K --> 9400	Colour & Neutral White --> R940	
		Tuneable white - 2700°K-4000°K --> 2740	* Contact us for other requirements *	

	Mounting	* <u>Canopy:</u>	<u>Floor Standing:</u>	
		Single Point --> CS	Marble Base --> FM	
		Multiple Point --> CM	Granite Base --> FG	
		Vertical --> CV	Thick Aluminium Base --> FA	MM
			Thin & Wide Steel Base --> FS	
		* <u>Recessed No Canopy:</u>	<u>Direct surface mounting:</u>	
		Multiple Point --> MM	Flush Mount --> D0	
		Vertical --> MV	** Foot Mount --> DF	
		* Cable Length	** Foot Length	
		2.5m --> 025	6cm --> 6	025
	4m --> 040	12cm --> 12		
	6m --> 060			

	Control	Dimmable - W/o Dimmer --> 00	1-10V --> 40	
		Simple Remote --> 10	0-10V --> 50	20
		DALI / Push dim compatible --> 20	Casambi --> 60	
		DMX --> 30		

Full model number example



BU150 - HR9011 9400 - MM025 - 20