



Model Name Cube In & Out 120
 Materials Aluminium frame, PC diffuser
 Design by Peter Danczkay

Luminaire dimensions 120x120x5 cm
 Profile dimensions 50x30 mm
 Luminaire weight 5.6 kg

Light Direction In & Out




Net Lumens output 19460 lm
 Lumens LED output 32430 lm

LED Life 50 000 hrs L80/B30
 Warranty 1+2 years



Voltage (constant voltage) 24 V
 Amperes / Watts 9.1 A / 217 W



Technical data is subject to change.

Document version v220415

	Light Direction	In	--> CI	Down	--> CD	CH
		Out	--> CO	In & Out	--> CH	
		Up	--> CU	Up & Down	--> CV	

	Size	Standard Sizes *				
		60 cm	--> 60	90 cm	--> 90	120
		120 cm	--> 120	150 cm	--> 150	

* Other sizes available upon request

	Finish	Premium	-->	P					
		Deco Black	Pearl White	Golden Eye	Silver Chalice	Ruby Red	Twilight Blue	Champagne Brown	Forest Green
		10 10M	20 20M	30 30M	40 40M	50 50M	60 60M	70 70M	80 80M

* Use XX for high gloss finish and XXM for matt

** Additional custom colours can be selected by providing RAL or auto colour code

Highline	-->	H				
Gold	-->	R1036	White	-->	R9016	HR9011
Silver	-->	R1036	Black	-->	R9011	

* Use M suffix for matt

** Any RAL colour, or special effects Powder coating available upon request

	LED Colour	Warm White (Standard) - 3000°K	-->	9300	Full Colour	-->	RGB	9400
		Extra Warm White - 2700°K	-->	9270	Colour & Warm White	-->	R930	
		Neutral White - 4000°K	-->	9400	Colour & Neutral White	-->	R940	
		Tuneable white - 2700°K-4000°K	-->	2740	* Contact us for other requirements *			

	Mounting	* <u>Canopy:</u>		<u>Floor Standing:</u>				
		Single Point	-->	CS	Marble Base	-->	FM	
		Multiple Point	-->	CM	Granite Base	-->	FG	
		Vertical	-->	CV	Thick Aluminium Base	-->	FA	
					Thin & Wide Steel Base	-->	FS	
							MM	
			* <u>Recessed No Canopy:</u>		<u>Direct surface mounting:</u>			
			Multiple Point	-->	MM	Flush Mount	-->	D0
			Vertical	-->	MV	** Foot Mount	-->	DF
			* Cable Length		** Foot Length			
		2.5m	-->	025	6cm	-->	6	
		4m	-->	040	12cm	-->	12	
		6m	-->	060			025	

	Control	Dimmable - W/o Dimmer	-->	00	1-10V	-->	40
		Simple Remote	-->	10	0-10V	-->	50
		DALI / Push dim compatible	-->	20	Casambi	-->	60
		DMX	-->	30			

Full model number example



CH120 - HR9011 9400 - MM025 - 20